UV-28 Plus APP Programming Guide

- **1. APP Installation** [Radio Frequency Programmer]
- 1) Android APP
- Scan QR code



• Download Link:

https://baofeng.s3.amazonaws.com/Baofeng_UV-28_Plus_APP_programming_software.zip

boorengradio.com *The Android App will ask for permission. The permission for Location is necessary for Bluetooth connection. Others can be denied.

- 2) iOS APP (iPhone)
- Scan QR code



• Download Link:

https://apps.apple.com/cn/app/radio-frequency-programmer/id6471483529

2. Radio Reading

1) Open UV-28 Plus, enter the menu and then turn on Bluetooth function.





2) Open Bluetooth of your smartphone, open "Radio Frequency Programmer"



Baofeng UV-28 Plus

3) Choose model "UV-28 Pro Series".

Radio Frequency Programmer	Radio Frequency Programmer			Radio Frequency Programmer			
UV5R Series	<	INVOOD Ci		<	BaoFeng		
0	JJCC	SHX	BaoFeng	5RM Series	UV-17/21/25 Pron(LMH)	K5PLUS(M)	
	KD	QuanSheng	TP	UV-S9 Plus	9RPro Series	UV9RPro V1 Series	
Radio Not Bluetooth Connected	TDX	RT		AR-152 Series	480 Series	666 Series	
				WP970 Series	UV5RH Series	UV25 Series	
() Connect				M-BPro Series	UV17 Series	UV-18 Pro(L)	
Select Profile				UV21 Series	UV21-GPS Series	GMRS21	
David 2 Write				UV20 Series	UV265 O Series	UV18Pro Series	
				UV17Pro Series	UV25Pro Series	UV26Pro Series	
				BF-T20	UV-5RH GMRS	ANIO Series	
				UV 32Pro Series	UV28Pro Series	UV/21Pro Sol	
Home Profile Settings	Home	Profile	© Settings	Home	Service Profile	© Settings	

4) Click "connect", match UV-28 Plus radio. Then click to select and wait 10 seconds till it shows Connection Successful.

			<	Bluetooth Device List	0	<	Bluetooth Device List	¢	
Radio Frequence	cy Programmer		walkie	-talkie		walkie	-talkie		
UV28Pro Series			3C:AB:72:1C:E6:FD			3C:AB:72:1C:E6:FD			
		(1)							
Radio No ⁻	t Bluetooth C	onnected							
		() Connect					Commontion Commonful		
							Connection Successful		
	UV-28 Plus								
Ь		Ô							
Home	Profile	Settings							

Baofeng UV-28 Plus

5) Back to homepage as Bluetooth paired. Click Read, it will start to loading, and you will get into Case Detail.

Radio Frequency Programmer	Radio Frequency Programmer	UV-28 Plu	S Profile
UV28Pro Series	UV28Pro Series	Channel Freq Mode	Optional Features
		Zone	1 💌
(2)	0	Current Channel Number	1 🔻
		Channel Name	Baofeng
walkie-talkie	walkie-talkie	RX Frequency(MHZ)	146.02500
3C:AB:72:1C:E6:FD	3C:AB:72:1C:E6:FD	TX Frequency(MHZ)	146.02500
		RX CTCSS/DCS	OFF 🔻
		TX CTCSS/DCS	OFF 🔻
() Disconnect	13% Disconnect	SigCode	1 💌
Select Profile	Select Profile	PTT-ID	OFF 🔻
		Power	Low 🔻
Read Write	Read Write	W/N	Wide
		Mute Way	QT/DQT 🔻
		BusyLockout	OFF
		Scan Add	9 des
		Clear Default	SAVE
Home Profile Settings	Home Profile Settings	Home Profile	Settings
Write and Save			- 0
write and Save			•

3. Write and Save

Click SAVE and name your cases after detail editing. Back to HOME, choose the case which you need to write into the radio. Click Write to programming.



*Note: If you want re-program the radio, you need restart Bluetooth of the radio. And run again the APP.